

APPENDIX B-245

DSC CONTROL TABLE DOCUMENT

1. The DSC Control Table is established mechanically to automatically assign MILSTRIP Document Numbers, Recommended Buy Numbers and Violation Control Numbers as required by various chapters in this volume. The following entries may be made to manually establish, change or delete data when applicable to Table Keys 0 and 02 only or to request a DSC Control Table Printout, appendix F-254. Table Keys 03, 04 and 05 are mechanically controlled and may not be locally changed (see notes).

2. This document can be processed through SAMMSTEL by entering the Verb SODE as described in DLAH 4745.2, Volume I, DLA Remote Users Handbook.

3. The following fields apply:

<u>FIELD</u> <u>LEGEND</u>	<u>FIELD</u> <u>POSITIONS</u>	<u>EXPLANATION/INSTRUCTIONS</u>
Document Identifier Code	1-3	Enter DIC ZLX.
Routing Identifier Code	4-6	Enter RIC of processing DSC.
Blank	7	Leave blank.
Table Key	8-9	*Enter Table Key as follows: 01 - MILSTRIP Document Number (numeric). 02 - MILSTRIP Document Number (alpha-betic).
Blank	10-19	Leave blank.
Beginning Serial Number	20-23	*Enter 4 alpha/numerics as applicable (applies to Table Keys 01 and 02). Cannot be alphas between TZZZ and VAAA. Must be less than Ending Serial Number.
Blank	24-26	Leave blank.

<u>FIELD LEGEND</u>	<u>FIELD POSITIONS</u>	<u>EXPLANATION/INSTRUCTIONS</u>
Maximum (Ending) Serial Number	27-30	*Enter 4 alpha/numerics as applicable (applies to Table Keys 01 and 02). Cannot be alphas between TZZZ and VAAA. Must be Beginning Serial Number.
Blank	31-76	Leave blank.
Output Routing Code	77-78	Enter ORC of individual preparing the input.
Action Code	79-80	Enter Action Code from appendix A-42 as follows: AA - Change (overlay) entry in table. AC - Print DSC Control Table Printout, appendix F-254.

*Entries not required when Action Code AC is entered in pos. 79-80.

NOTES 1 and 2 provided for information only:

NOTE 1: Table Keys 03 - Recommended Buy Number and 04 - Violation Control Number are established by the computer, under the following configuration and may not be changed by manually prepared entries. Table Key 03 - Beginning Serial Number 000001; Ending Serial Number 999,999. Table Key 04 - Beginning Serial Number AAA (excluding letters I and O); Ending Serial Number 999.

NOTE 2: Table Key 05 is established by the computer - Used to assign document numbers to Recommended Disposal Transaction/Disposal Release Orders. Also to be used for Redistribution Orders (DIC A2_) when bulk redistribution is directed by DIC ZLU input.

1 - DIC ZLC transactions for NSNs with shelf-life, entry in pos. 20 and pos. 27.

2 - DIC ZLC transaction for NSNs with no shelf-life, entry in pos. 20 and pos. 27 numeric zero.

3 - DIC A2_ transactions created by ZLU input, entry in pos. 20 and 27 numeric other than zero.

Balance of entries pos. 41-43 (serial number) for the above transactions may be alpha, numeric, or alpha/numeric mix.